



START

Are you going to install a 3rd Gen Core processor?

No

Update the board to the latest BIOS version, using one of these methods:

- [Express Update](#)
- [iFlash Update](#)

Yes

Find:

- Board AA#
- BIOS version
- Intel® ME firmware version

(See instructions)

Compare board AA# to the 3rd Gen-Ready and 3rd Gen-Capable columns in [Table 1](#)

Is the board's AA# a 3rd Gen-Ready version or later?

Yes

Install 3rd Generation Core processor

No

This board does not support 22nm processors

Yes

Is the board's AA# earlier than the 3rd Gen-Capable version?

No

Is the board's BIOS version at the 3rd Gen-Transition BIOS version?

Yes

Is the board's BIOS version at the 3rd Gen-Ready BIOS version or later?

No

With current generation processor installed, update the board to the 3rd Gen-Ready BIOS version or later, using one of these methods:

- [Express Update](#)
- [iFlash Update](#)

No

With a current generation processor installed, update the board to the 3rd Gen-Transition BIOS version, using one of these methods:

- [Express Update](#)
- [iFlash Update](#)

Yes

Is the board's Intel® ME firmware version 8.x or later?

No

With current generation processor installed, update the board to the 3rd Gen-Ready BIOS version or later, using [Recovery Update](#) method

Yes

Instructions for finding alternate assembly number (AA#), BIOS version, and Intel® ME firmware version

During boot, enter the BIOS setup by pressing **F2**.

The board's current BIOS version is shown at the top of the **Main** menu. Then click **System Identification Information**.

System Setup	
Main	Configuration Performance Security Power Boot Exit
BIOS Version	BLH6710H.86A.0076.2010.1115.1959
Processor Type	Intel(R) Core(TM) i3-2120 CPU @ 3.30GHz
Active Processor Cores	<ALL>
Intel® Hyper-Threading Technology	<Enable>
Host Clock Frequency	100 MHz
Processor Turbo Speed	3.30 GHz
Memory Speed	1333 MHz
L2 Cache RAM	2 x 256 KB
L3 Cache RAM	3 MB
Total Memory	1 GB
DIMM3 (Memory Channel A Slot 0)	Not Installed
DIMM1 (Memory Channel A Slot 1)	1 GB
DIMM4 (Memory Channel B Slot 0)	Not Installed
DIMM2 (Memory Channel B Slot 1)	Not Installed
<u>System Identification Information</u>	
System Date	<Wed 01/25/2012>
System Time	<02:44:09>

The board's AA# and Intel® ME firmware version are shown on the **System Identification Information** screen.

System Setup	
Main	
System Identification Information	
System Information	
Manufacturer	
Product Name	
Version	
Serial Number	
UUID	7E9D8539-2668-E011-A698-00E04CA04AED
Desktop Board Information	
Manufacturer	Intel Corporation
Product Name	DH67BI
Version	AAG10189-205
Serial Number	BTBL1160030Z
Chassis Information	
Manufacturer	
Version	
Serial Number	
Asset Tag	
Processor Signature	000206A7
	Family 6h Model 2Ah Stepping 7h
Microcode Update Revision	00000006
Onboard LAN MAC Address	E0-69-95-72-0F-1D
<u>Intel® Management Engine Information</u>	
Intel® Management Engine Firmware	7.0.1.1141

Table 1

Board	3rd Gen-Ready AA#s	3rd Gen-Capable AA#s	3rd Gen-Transition BIOS version	3rd Gen-Ready BIOS version
DZ68DB	AAG27985-105 or later	All	DBZ6810H.86A.0032	DBZ6810H.86A.0040 or later
DZ68BC	AAG30742-403 or later	All	BCZ6810H.86A.0028	BCZ6810H.86A.0035 or later
DZ68ZV	AAG41861-302 or later	AAG41861-301	BGP6710J.86A.2111	BGP6710J.86A.2161 or later
DP67BG	AAG10491-401 or later	AAG10491-400	BGP6710J.86A.2111	BGP6710J.86A.2161 or later
DP67DE	AAG10217-304 or later	AAG10217-301	BAP6710H.86A.0072	BAP6710H.86A.0077 or later
DP67BA	AAG10219-304 or later	AAG10219-301	BAP6710H.86A.0072	BAP6710H.86A.0077 or later
DH67GD	AAG10206-210 or later	AAG10206-206	BLH6710H.86A.0132	BLH6710H.86A.0151 or later
DH67CL	AAG10212-210 or later	AAG10212-206	BLH6710H.86A.0132	BLH6710H.86A.0151 or later
DH67CF	AAG10215-207 or later	AAG10215-204	BLH6710H.86A.0132	BLH6710H.86A.0151 or later
DH67BL	AAG10189-211 or later	AAG10189-206	BLH6710H.86A.0132	BLH6710H.86A.0151 or later
DH67BLR	AAG44434-201 or later	All	BLH6710H.86A.0132	BLH6710H.86A.0151 or later
DH61ZE	AAG43004-201 or later	All	BEH6110H.86A.0035	BEH6110H.86A.0041 or later
DH61WW	AAG23116-206 or later	AAG23116-204	BEH6110H.86A.0035	BEH6110H.86A.0041 or later
LADH61WW	AAG39552-206 or later	AAG39552-204	BEH6110H.86A.0035	BEH6110H.86A.0041 or later
DH61SA	AAG38870-204 or later	All	BEH6110H.86A.0035	BEH6110H.86A.0041 or later
LADH61SA	AAG38871-204 or later	All	BEH6110H.86A.0035	BEH6110H.86A.0041 or later
LADH61SAR	AAG44435-202 or later	All	BEH6110H.86A.0035	BEH6110H.86A.0041 or later
DH61HO	All	All	N/A	All
DH61DL	AAG14066-205 or later	All	BEH6110H.86A.0035	BEH6110H.86A.0041 or later
DH61CR	AAG14064-207 or later	AAG14064-204	BEH6110H.86A.0035	BEH6110H.86A.0041 or later
DH61BE	AAG14062-209 or later	AAG14062-206	BEH6110H.86A.0035	BEH6110H.86A.0041 or later
DH61AG	AAG23736-503 or later	All	AGH6110H.86A.0037	AGH6110H.86A.0039 or later

The following Intel® Desktop Boards will not include support for 3rd Generation Intel® Core™ processors:

- DH61KVCH
- DH61SKCH
- DB65AL
- DH67VR
- DQ67SW
- DQ67OW
- DQ67EP