



Previously Logo'd Motherboard Program (PLMP)

Intel® Desktop Board

DG45FC

PLMP Report

7/23/2010

Purpose:

This report describes the DG45FC Previously Logo'd Motherboard Program testing run conducted by Intel Corporation.

THIS TEST REPORT IS PROVIDED "AS IS" WITH NO WARRANTIES WHATSOEVER, INCLUDING ANY WARRANTY OF MERCHANTABILITY, FITNESS FOR ANY PARTICULAR PURPOSE, OR ANY WARRANTY OTHERWISE ARISING OUT OF ANY PROPOSAL, SPECIFICATION OR SAMPLE.

Information in this document is provided in connection with Intel products. No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document or by the sale of Intel products. Except as provided in Intel's Terms and Conditions of Sale for such products, Intel assumes no liability whatsoever, and Intel disclaims any express or implied warranty, relating to sale and/or use of Intel products including liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright or other intellectual property right. Intel products are not intended for use in medical, life saving, or life sustaining applications.

Intel retains the right to make changes to its test specifications at any time, without notice.

The hardware vendor remains solely responsible for the design, sale and functionality of its product, including any liability arising from product infringement or product warranty.

Intel® Core™ i7 and Intel® are trademarks of Intel Corporation in the U.S. and other countries.

*Other names and brands may be claimed as the property of others

Copyright © 2009, Intel Corporation. All rights reserved.

Contents

- Introduction4**
 - Terms and Definitions.....4
- Desktop Board Configuration5**
 - Desktop Board DG45FC Final Configuration Report: Completion of PLMP5
 - Board Information.....5
 - Product Code.....5
 - Processor5
 - Motherboard5
 - System Memory.....5
 - Power Management.....5
 - Operating System Tested.....5
 - Onboard Integrated Devices and Driver for Windows 7 32-bit and 64-bit.....6
 - Windows Logo Kits Used (WLK)6
 - Errata and Contingencies7
 - Test Notes8

Introduction

Terms and Definitions

Term	Definitions
WHQL	Windows* Hardware Qualification Lab
WLK	Windows Logo Kits
PLMP	Previously Logo'd Motherboard Logo Program. For further information see: http://www.microsoft.com/whdc/hwtest/default.msp
AP Machine	Audio Precision Machine
Winqual	Windows Qualification
MSFT Tested Product List	Tested Products List. You can view the Windows Marketplace for tested products list at: http://winqual.microsoft.com/HCL/ProductList.aspx?m=v&cid=105&q=s

Desktop Board Configuration

Desktop Board DG45FC Final Configuration Report: Completion of PLMP

Data in this section reflects system configuration at time of PLMP submission.

Board Information

Product Code ¹	BIOS String/Model	Technologies NOT Logo'd (yet)
DG45FC	IDG4510H.86A.0129.2010.0408.0910	N/A - all technologies logo'd
Processor		
Speed	3.33GHz	
Family	Intel® Core™2 Duo E8600	
Bus Speed	1333 MHz	
Motherboard		
Board AA #	E27730	
Board FAB #	308	
* This report applies to the production FAB revision; Please consult your Intel Corporation representative to clarify the motherboard revision you intend to perform logo testing if not the same.		
System Memory		
Speed	Dual Channel, DDR2, 800MHz	
Memory Type	DIMM	
Connector Type	DDR2, 240 Pin	
Power Management		
BIOS Default	S3	
Operating System Tested		
	Check Tested	Comments
Windows 7 and 64-bit	<input checked="" type="checkbox"/>	Windows 7 Ultimate
Windows Vista and 64-bit	<input type="checkbox"/>	Vista Ultimate with Service Pack 2
Windows Vista Basic and 64-bit	<input type="checkbox"/>	Vista Basic with Service Pack 2

¹ These are the product names to enter in the "Submission ID of previously logo'd qualified PC system or server" field during your "System Using a Previously Logo'd Motherboard" submission to Microsoft.

Onboard Integrated Devices and Driver for Windows 7 32-bit and 64-bit

Technology	OS	Version	Package version
Chipset Update Utility Intel® Chipset Software Utility	Windows 7	9.1.1.1025	9.1.1.1025
	Windows 7 64-bit	9.1.1.1025	9.1.1.1025
Graphics Intel® Graphics Media Accelerator	Windows 7	8.15.10.2119	15.17.4.2119
	Windows 7 64-bit	8.15.10.2119	15.17.4.64.2119
Audio Realtek	Windows 7	6.10.6224.6	6224.6
	Windows 7 64-bit	6.10.6224.6	6224.6
LAN Realtek	Windows 7	10.1.6.0	15.1
	Windows 7 64-bit	10.1.6.0	15.1

Windows Logo Kits Used (WLK)

Microsoft website: <http://www.microsoft.com/whdc/DevTools/WDK/DTM.msp>

Please check regularly for test kit updates from Microsoft. Please ensure latest filters updated prior to WHQL run.

Operating Systems	Notes	WHQL Testkit
Windows Vista Windows Vista 64-bit	WLK1.5 for Windows Vista SP2	WLK1.5 for Windows Vista SP2
Windows 7 Windows 7 64-bit	WLK1.5 for Windows 7	WLK1.5 for Windows 7

Errata and Contingencies

Operating System	Failing Test	Expiry Date	ID Number	Type	Error Description
Windows 7 Windows 7 64-bit	PCI Hardware Compliance Test For System	12/1/2010	401	Erratum	The following PCI Compliance test failure is acceptable: Bit 15 (Bridge Configuration Retry Enable) in the Device Control register (offset 8h) in the PCI Express Capability table must be read-only and always return 0 as it is reserved for devices other than PCI Express to PCI/PCI-X Bridges. Assertion 13A41D3E-2576-41DC-A67C-525DA3637CEA This failure is acceptable because this is a PCIe 1.1 feature and the WLP requires compliance with only PCIe 1.0a.
Windows 7 Windows 7 64-bit	Graphics HDMI System Test (Manual)	12/31/2010	1945	Erratum	Failure is due to the ELDv2 PortId not matching the graphics adapter LUID. This cannot be enforced currently. In the future, video drivers will be required to program the ELDv2 PortId with either, The AdapterLUID for the corresponding display adapter - OR- 0
Windows 7 Windows 7 64-bit	UAA Test - Vista or Server08 (System)	6/1/2010	1288	Erratum	Error: attempted to set unsupported EPT 0b10 (Reserved); previous value was 0b01 (Reserved); response was 0b10 (Reserved) For unsupported EPTs, the pin must either retain the previous value or take the value of 0b00 (Native). See HD Audio specification section 7.3.3.13.
Windows 7 Windows 7 64-bit	UAA Test - Vista or Server08 (System)	6/1/2010	1348	Erratum	Errata 1348 Preview Errata - ASP Channel Mapping The Intel HD Audio DCN 34-A2, HDMI/Multichannel, defines a mapping between digital converter channels and HDMI slots; see section 7.3.3.41 of the DCN. Much of the verbiage is generalized in DCN 36-A to apply equally to DisplayPort slots. The latest versions of all DCNs are posted on Intel's HD Audio standards page: http://www.intel.com/standards/hdaudio/ The default mapping from digital converter channels to slots is expected to be 0 --> 0, 1 --> 1, 2 --> ***3***, 3 --> ***2***, 4 --> 4, 5 --> 5, 6 --> 6, and 7 --> 7.
Windows 7 Windows 7 64-bit	UAA Test - Vista or Server08 (System)	6/1/2015	513	Erratum	UAA Test requires the Traffic Priority bit to be read/write - however there are two specs that apply, and they conflict. One says the bit must be read/write, the other says it must be read-only. Contact has been made with the author of both specs (Intel) but until this point is clarified we cannot fail submissions containing this test failure.
Windows 7 Windows 7 64-bit	Class Driver AC3 Test - Win7 (System)	6/30/2025	1256	Erratum	Run AC3 test on a system with the Microsoft HD Audio class driver installed. Expected results: All AC3 kernel streaming data ranges should advertise MinimumBitsPerSample = 16 and MaximumBitsPerSample = 16. Actual results: HD Audio class driver sometimes advertises MaximumBitsPerSample = 24.

Test Notes

Operating System	Test	Description
Windows 7 and Vista	BIOS download	Internal: http://bios.intel.com/downloads/ External: http://www.intel.com/ click on Support and Download
Windows 7 and Vista	BIOS setup	Please make sure the BIOS setting are as below, otherwise use default settings. System Date and Time: Current date and time Peripheral Configuration: Enable all onboard component Drive Configuration: Set to IDE Chipset Configuration: Enable HPET ACPI Suspend State: Set to <S3 State> Boot Device Priority: set <Hard Disk Driver> to first
Windows 7 and Vista filter update	WLK WHQL test	http://winqual.microsoft.com/member/SubmissionWizard/LegalExemptions/filterupdates.cab
Special H/W that use to PASS the test	None	None