CPU	PA-2000	PA-2001	PA-2002	PA-2005	PA-2006_PCB2.1	PA-2006_PCB2.1_with_USB	PA-2007
PCB REVISION	1.32	1.1	1.21	1.3/1.31	2.1	2.1(USB)	1.1/1.2
Pentium P54C-75	V	V	V	V	V	V	V
Pentium P54C-90	V	V	V	V	V	V	V
Pentium P54C-100	V	V	V	V	V	V	V
Pentium P54C-120	V	V	V	V	V	V	V
Pentium P54C-133	V	V	V	V	V	V	V
Pentium P54C-150	*	V	V	V	V	V	V
Pentium P54C-166	*	V	V	V	V	V	V
Pentium P54C-200	*	*	V	V	V	V	V
Pentium P55C-166	X	X	X	V	V	V	V
Pentium P55C-200	X	X	X	V	V	V	V
Pentium P55C-233	X	X	X	V	V	V	V
Pentium CTB-150	*	X	*	V	V	V	V
Pentium CTB-166	*	X	*	V	V	V	V
Cyrix 6x86-P133+	*	*	V	V	V	V	V
Cyrix 6x86-P150+	*	*	V	V	V	V	V
Cyrix 6x86-P166+	*	*	*	V	V	V	V
Cyrix 6x86L-P166+	*	*	*	V	V	V	V
Cyrix 6x86L-P200+	X	X	X	FOR V 1.31	V	V	!
Cyrix 6x86MX-PR166	X	X	X	V	*	*	V
Cyrix 6x86MX-PR200 (66x2.5)	X	X	X	V	*	*	V
Cyrix 6x86MX-PR200 (75X2)	X	X	X	FOR V 1.31	*	*	!
AMD K5-PR90	V	*	V	V	V	V	V
AMD K5-PR100	V	*	V	V	V	V	V
AMD K5-PR120	V	*	V	V	V	V	V
AMD K5-PR133	V	*	V	V	V	V	V
AMD K5-PR150	*	*	*	V	V	V	V
AMD K5-PR166	X	X	*	V	V	V	V
AMD K5-PR200	X	X	*	*	*	*	V
AMD K6-166	X	X	X	V+	V+	V+	V
AMD K6-200	X	X	X	V+	V+	V+	V
AMD K6-233	X	X	X	*	*	*	V

Remarks:

*=not tested

V+=only with hardware modification

X=not compatible

!=unofficial

FIC Technical Support