

abit *Engineered*


- | Press Center
- | BIOS Guide
- | CPU support
- | Downloads
- BIOS
- Drivers
- Utilities
- Manuals
- | FAQs
- | Awards
- | Contact Us
- | About Us
- R&D
- Customer Service
- Copyright info
- | HOME
- Newsletter Sign-Up
-
- Subscribe/ Unsubscribe
- Search
-
-
- Product
- FAQs
- News
- Award

MOTHERBOARD Socket 478

Browse by processor

-- Select One -- ▾

BD7-E



845D Based Pentium4 Motherboard
10/100M LAN, ATA100, AGP4X, 2-ch Audio

Product Information

- [Overview](#)
- [Specifications](#)
- [Test Reports](#)

Support Information

- [FAQs](#)
- [BIOS](#)
- [Driver](#)
- [Utility](#)
- [Manual](#)

Specifications

- CPU**
- Supports Intel Pentium® 4 Socket 478 processors with 533 MHz FSB
 - Supports Intel Pentium® 4 Socket 478 processors with 400 MHz FSB

- Chipset**
- Intel 845D/ICH2 chipset
 - Supports AGP 4X (1.5V device only)
 - Supports Universal Serial Bus (USB 1.1)

- Memory**
- Two 184-pin DDR DIMM sockets (Un-buffered Non-ECC DIMM)
 - Supports DDR 333 (OC) / DDR 266 / DDR 200 (Max. 2GB)

- Audio**
- 2-Channel AC97 CODEC on board

- LAN**
- On board 10/100M PCI Ethernet Controller

- System BIOS**
- Supports Advanced Configuration Power Interface (ACPI)
 - Supports Desktop Management Interface (DMI)

- Internal I/O Connectors**
- 1 x AGP slot
 - 5 x PCI slots
 - 1 x Floppy Port supports up to 2.88MB
 - 2 x Ultra ATA 100/66/33 Connectors
 - 1 x USB 1.1 header
 - 1 x CD-IN, 1 x AUX-IN

- Back Panel I/O**
- 1 x PS/2 Keyboard, 1 x PS/2 Mouse
 - 1 x Serial Port connector, 1 x Parallel Port connector
 - 1 x Audio connector (Front Speaker, Line-in, MIC-in)
 - 2 x USB Connectors, 1 x RJ-45 LAN Connector

- Miscellaneous**
- ATX form factor (305 x 190 mm)

- Package**
- User's Manual x 1
 - Ultra DMA cable x 1
 - FDD cable x 1
 - Support CD x 1
 - I/O shield x 1
 - Jumper Setting Label x 1