

abit Engineered


- Press Center
- BIOS Guide
- CPU support
- Download
- BIOS
- Drivers
- Utilities
- Manuals
- FAQs
- Awards
- Conabitt
- Abobitt
- R&D
- Customer Service
- Copyright info
- HOME
- Newsletter Sign-Up
- Please enter a valid
- Subscribe/ Unsubscribe
- Search
- Product
- FAQs
- News
- Award

MOTHERBOARD Socket 478

Browse by processor

-- Select One -- ▾

BE7II



845PE Based Pentium4 Mainboard
FSB533, DDR333, ATA100, AGP4X, USB2.0,
6 CHAudio

Product Information

- [Specifications](#)
- [Test Reports](#)

Support Information

- [FAQs](#)
- [BIOS](#)
- [Driver](#)
- [Utility](#)
- [Manual](#)

Specifications

- >> CPU**
 - Supports Intel Pentium® 4 Socket 478 processors with 533/400 MHz FSB
 - Supports Intel Hyper-Threading Technology
- >> Chipset**
 - Intel 845PE/ICH4 chipset
 - Supports Hi-Speed Universal Serial Bus (USB 2.0)
- >> Memory**
 - Two 184-pin DDR DIMM sockets (Un-buffered Non-ECC DIMM)
 - Supports 2 DIMM DDR 333/266/200 (Max. 2GB)
- >> Audio**
 - 6-Channel AC 97 CODEC on board
 - Professional digital interface
- >> LAN**
 - On board 10/100Mbps PCI Ethernet Controller
- >> ABT Engineered**
 - ABIT CPU ThermalGuard™
 - ABIT FlashMenu™
 - ABIT EQ™
- >> Internal I/O Connectors**
 - 1 x AGP slot
 - 5 x PCI slots
 - 1 x Floppy Port supports up to 2.88MB
 - 2 x Ultra ATA 100/66/33 connectors
 - 2 x USB 2.0 headers
 - 1 x FP-Audio header
 - 1 x CD-IN, 1 x AUX-IN
- >> Back Panel I/O**
 - 1 x PS/2 Keyboard, 1 x PS/2 Mouse
 - 1 x Serial Port connector, 1 x Parallel Port connector
 - 1 x Audio connector (Front Speaker, Line-in, Mic-in)
 - 2 x USB connectors, 1 x RJ-45 LAN connector
- >> Miscellaneous**
 - ATX form factor (305 x 190 mm)
 - Hardware Monitoring - Including fan speed, voltages, CPU and system temperature
 - Supports Wake Up by LAN, Modem Ring, RTC Alarm, Keyboard and Mouse Power On
- >> Package**
 - User's manual x 1
 - Jumper setting label x 1
 - Ultra DMA cable x 1
 - FDD cable x 1
 - Support CD x 1
 - I/O shield x 1

