

abit Engineered™

| P r e s s C e
| B I O S G u i
| C P U s u p p
| D o w n l o a
BIOS
Drivers
Utilities
Manuals
| F A Q s
| A w a r d s
| C o n a b i t
| A b a b i t t
R&D
Customer Service
Copyright info
| H O M E
Newsletter Sign-Up


Subscribe/ Unsubscribe
Search

 Product
 FAQs
 News
 Award

MOTHERBOARD Socket 478

Browse by processor
-- Select One --

BE7re



Intel 845PE Based Pentium®4 ATX Mainboard
DDR333, 6 Channel Audio, USB 2.0, 10/100MLAN
SoftMenu™ Technology

Product Information

- [Overview](#)
- [Specifications](#)
- [News](#)
- [Test Reports](#)

Support Information

- [FAQs](#)
- [BIOS](#)
- [Driver](#)
- [Utility](#)

Specifications

CPU

- Supports Intel Pentium4 Socket 478 processors with 400/533 MHz Front Side Bus

Chipset

- Intel 845PE/ ICH4
- Supports Ultra DMA 33/66/100
- Accelerated Graphics Port connector supports AGP4X Interface (1.5V only)

Memory

- Three 184-pin DIMM sockets (unbuffered Non-ECC DIMM)
- Supports 2 DIMM DDR200/266/333 or 3 DIMM DDR200/266 (Max. 2GB)

Audio

- On board ALC650 6-Channel CODEC

USB 2.0

- Supports 6 Ports USB 2.0 at 480 Mb/sec transfer rate

LAN

- On board RTL8100B 10/100M PCI Fast Ethernet Controller

System BIOS

- SoftMenu™ Technology to set CPU parameters
- Supports Plug-and-Play (PNP)
- Supports Advanced Configuration Power Interface (ACPI)

Internal I/O Connectors

- 1 AGP slot, 5 PCI slots
- 1 x Floppy Port supports up to 2.88MB
- 2 x Ultra DMA 33/66/100 Connectors
- 2 x USB headers, 1 x IrDA header
- 1 x CD-IN, 1 x AUX-IN

Back Panel I/O

- 1 x PS/2 Keyboard, 1 x PS/2 mouse
- 2 x Serial Port connectors, 1 x Parallel Port connector
- 1 x S/PDIF Out connector
- Audio connectors (Center/Sub, Surround Speaker)
- Audio connectors (Front Speaker, Line-in, Mc-in)
- 2 x USB, 1 x RJ-45 LAN Connector

Miscellaneous

- ATX form factor
- Hardware monitoring - Including Fan speeds, Voltages, CPU and System environment temper