

**abit Engineered™**

- Press Center
- BIOS Guide
- CPU support
- Download
- BIOS
- Drivers
- Utilities
- Manuals
- FAQs
- Awards
- Contact Us
- Abroad
- R&D
- Customer Service
- Copyright info
- HOME
- Newsletter Sign-Up
- 
- Subscribe/ Unsubscribe
- Search
- Product
- FAQs
- News
- Award

MOTHERBOARD LGA775

Browse by processor

-- Select One -- ▼

**AG8re**



- LGA 775
- Intel® 915P
- FSB800
- Dual DDR400
- PCI Express
- Gigabit LAN
- SATA Matrix RAID
- IEEE1394
- 6ch Audio
- µGuru™ Tech



**Specifications**

**>> LGA775 CPU Socket**

- Designed for Intel® 90nm Prescott LGA775 processors with 800/533 MHz FSB
- Supports Intel Hyper-Threading Technology

**>> Express Chipset**

- Intel 915P / Intel ICH6R Express Chipset
- Supports Hi-Speed Universal Serial Bus (USB 2.0)

**>> Flexible Memory**

- Four 184-pin DIMM sockets (Un-buffered Non-ECC DIMM)
- Supports Dual channel DDR 400/333 (Max. 4GB)

**>> PCI Express x16 graphics**

- PCI Express x16 graphics delivers up to 8GB/s per direction for 3.5 times more bandwidth than AGP8X at 2.1GB/s

**>> PCI Express x1 I/O**

- PCI Express x1 I/O offers 500MB/s concurrently, over 3.5 times more bandwidth than PCI at 133MB/s

**>> SATA Matrix RAID**

- Four ports SATA 150 RAID 0/1, deliver higher performance and data protection
- Supports SATA AHCI, providing native command queuing and native hot plug

**>> 6 Channel Audio**

- On board Theater-class 6 Channels Audio
- Professional digital audio interface supports auto jack sensing and optical S/PDIF In/Out

**>> IEEE 1394**

- Supports 3 Ports IEEE 1394 at 100/200/400 Mb/s transfer rate

**>> Gigabit LAN**

- On board GbE Gigabit LAN controller supports 10/100/1000 BASE-T Ethernet

**>> ABT Engineered**

- ABIT µGuru™ Technology (ABIT OC Guru/ABIT EQ/ABIT Flash Menu/ABIT Black Box)
- ABIT CPU ThermalGuard™ Technology

**>> Internal I/O Connectors**

- 1 x PCI Express x16 slot
- 3 x PCI Express x1 slots
- 2 x PCI slots
- 1 x Floppy Port supports up to 2.88MB
- 4 x SATA 150 Connectors
- 1 x Ultra ATA 100/66/33 Connector
- 2 x USB 2.0 headers
- 2 x IEEE 1394 headers
- 1 x FP-Audio header

**Product Information**

- [Specifications](#)
- [News](#)
- [Awards](#)
- [Test Reports](#)

**Support Information**

- [FAQs](#)
- [BIOS](#)
- [Driver](#)
- [Utility](#)
- [Manual](#)

- 1 x CD-IN, 1 x AUX-IN

>> Back Panel I/O

- 1 x PS/2 Keyboard, 1 x PS/2 Mouse
- 1 x Serial Port connector, 1 x Parallel Port connector
- 1 x S/PDIF IN/OUT
- 1 x Audio connector (Center/Subwoofer, Rear Surround)
- 1 x Audio connector (Line Out, Line-in, MIC-in)
- 2 x USB Connectors, 1 x IEEE1394 Connector
- 2 x USB Connectors, 1 x RJ-45 GbE LAN Connector

>> Miscellaneous

- ATX form factor (305 x 230 mm)

>> Compatible Accessories

- [Guru Panel™](#)

Total Rows:8 Page:1/1

<a href="#">Model</a>	<a href="#">Logo</a>	<a href="#">Media</a>	<a href="#">Country</a>	<a href="#">Award</a>	<a href="#">Date</a>
<a href="#">AG8</a>		<a href="#">PC Perspective</a>	USA	<a href="#">Gold</a>	2005/02/14
<a href="#">AG8</a>		微電腦傳真	Taiwan	<a href="#">編輯推薦大獎</a>	2004/11/01
<a href="#">AG8</a>		<a href="#">IN4</a>	Poland	<a href="#">Quality</a>	2004/10/22
<a href="#">AG8</a>		<a href="#">TwojePC</a>	Poland	<a href="#">OK</a>	2004/10/07
<a href="#">AG8</a>		<a href="#">ClubCC</a>	USA	<a href="#">Recommended</a>	2004/09/15
<a href="#">AG8</a>		<a href="#">FrazPC</a>	Poland	<a href="#">Recommendation</a>	2004/08/31
<a href="#">AG8</a>		ComputerDIY	Taiwan	<a href="#">編輯推薦大獎</a>	2004/07/16
<a href="#">AG8</a>		Hardware.info	Netherlands	Silver	2004/07/01

Copyright© 2006 Universal ABIT Co., Ltd. All rights reserved.  
 Reproduction and distribution in any form without permission is strictly prohibited.  
 The abit logo is a registered trademark of abit.