

abit Engineered™

- | Press Center
- | BIOS Guide
- | CPU support
- | Downloads
- BIOS
- Drivers
- Utilities
- Manuals
- | FAQs
- | Awards
- | Contact Us
- | About Us
- R&D
- Customer Service
- Copyright info
- | HOME

Newsletter Sign-Up

Please enter a valid

Subscribe/ Unsubscribe

Search


- Product
- FAQs
- News
- Award

MOTHERBOARD Socket 939

Browse by processor

-- Select One -- ▼

AN8re



- Socket 939
- Nvidia® NF4
- PCI-Express
- NV SATA RAID
- NV GbE
- NV Firewall
- IEEE 1394
- ABIT µGuru™
- ABIT OTES™
- AudioMAX™

Specifications

- >> CPU**
- AMD Athlon 64/64FX & [Athlon 64 X2 dual-core](#) 939-pin K8 CPU with 2GHz system bus using Hyper Transport Technology
 - AMD CPU Cool 'n' Quiet Technology

- >> Chipset**
- NVIDIA NF4 single chip
 - Integrated NV Gigabit Ethernet and NV Firewall

- >> Memory**
- Four 184-pin DIMM sockets
 - Support 4 DIMM Dual DDR 400/333/266 non-ECC memory
 - Support 4 DIMM up to 8GB Max.

- >> ABIT Engineered**
- ABIT µGuru™ Technology
 - ABIT OTES™ Technology
 - ABIT AudioMAX™ Technology
 - ABIT CPU ThermalGuard™ Technology

- >> NV SATA RAID**
- Supports SATA150 RAID 0/1/0+1 JBOD

- >> NV GbE LAN**
- NVIDIA Gigabit Ethernet via NF4

- >> NV Firewall**
- Native NVIDIA Firewall via NF4

- >> IEEE 1394**
- Support IEEE 1394 at 400/200/100 Mb/s transfer rate

- >> Audio**
- 5.1-channel Audio Card
 - Optical S/P DIF In/Out

- >> Internal I/O Connectors**
- 1 PCI-E X16 slot, 2 PCI-Express X1 slots
 - 3 PCI slots, 1 x ABIT Audio slot
 - 1x Floppy Port supports up to 2.88 MB
 - 2 x Ultra DMA 33/66/100/133 Connectors
 - 4 x SATA 150 Connectors
 - 3 x USB headers, 1 x IEEE1394 header

- >> Back Panel I/O**
- 1 x IEEE1394 Connector
 - 1 x PS/2 Keyboard, 1 x PS/2 mouse
 - 4 x USB+ 1 x RJ-45 LAN Connector

- >> Form Factor**
- ATX form factor 305 x 245mm

Product Information

- [Specifications](#)
- [News](#)
- [Test Reports](#)

Support Information

- [FAQs](#)
- [BIOS](#)
- [Driver](#)
- [Utility](#)
- [Manual](#)

Compatibility Information

- [CPU](#)

>> Package

- 1 x Audio Card
- 1 x Back panel I/O shield
- 4 x SATA signal cables
- 1 x ATA 133 IDE Cable, 1 x FDD cable
- 1 x USB2.0 + IEEE1394 cable
- 1 x A5 standard User's Manual
- 1 x A5 µGuru User's Manual
- 1 x B5 multilingual Quick Installation Guide
- 1 x CD title, 1 x SATA Driver Disk
- 1 x Jumper Setting Label

>> Compatible Accessories

- [Guru Panel™](#)

Copyright© 2006 Universal ABIT Co., Ltd. All rights reserved.
Reproduction and distribution in any form without permission is strictly prohibited.
The **abit** logo is a registered trademark of **abit**.