

TOTAL MEMORY	BANK 0 (30-PIN)	BANK 1 (72-PIN)	BANK 2 (72-PIN)
6MB	256K x 4	4M x 1	1M x 1
	256K x 4	1M x 1	4M x 1
	1M x 4	1M x 1	1M x 1
8MB	1M x 4	4M x 1	
	1M x 4		4M x 1
		4M x 1	4M x 1
9MB	256K x 4	4M x 1	4M x 1
	1M x 4	1M x 1	4M x 1
	1M x 4	4M x 1	1M x 1
12MB	1M x 4	4M x 1	4M x 1
16MB	4M x 4		
		16M x 1	
			16M x 1
17MB	256K x 4	16M x 1	
	256K x 4		16M x 1
		1M x 1	16M x 1
		16M x 1	1M x 1
	4M x 4	1M x 1	
	4M x 4		1M x 1
18MB	256K x 4	1M x 1	16M x 1
	256K x 4	16M x 1	1M x 1
	4M x 4	1M x 1	1M x 1
20MB	1M x 4	16M x 1	
	1M x 4		16M x 1
	4M x 4	4M x 1	
	4M x 4		4M x 1
		4M x 1	16M x 1
		16M x 1	4M x 1

Table 3-1. DRAM Configurations (Continued)